十度(SD-P14)说明书 128G双铜+风琴折 420*100MM

十度音响



SD-P14

使用说明书

USER MANUAL

产品尺寸图



注意事项

电池（电池组或组合电池）不得暴露于阳光、火源或类似的过热环境中。如果电池未按正确方式更换，可能存在爆炸危险，请务必使用相同或等效类型的电池进行更换。本产品不随附电源适配器，消费者通过电源适配器充电时，应购买经认证且符合标准要求的电源适配器。

产品介绍

音箱功能按键示意图





1. 模式切换键
2.TWS配对键
3. 多功能控制键
4.高音加/减键
5. 电量查询键
6. 灯光键
7. 低音加/减键
8. AUX接口
9.USB接口
10. TF卡槽
11. Type-C接口

操作指南

音箱功能按键说明

1. 模式切换键：短按切换（蓝牙/U盘/TF卡/LINEIN）。

2. TWS配对键：短按断开蓝牙重新进入配对状态；长按一台设备蓝牙按键2s，进入TWS配对或断开。

3. 多功能控制键：长按（中间键2S）开/关机；单击（中间键）暂停/播放/来电接听/挂断；上下推（上一曲/下一曲）；左右推（调节音量大小）。

4. 高音加/减键：短按/长按高音加/减（共10级）。

5.电量查询键：短按显示电量，电量5秒后自动熄灭。

6. 灯光键：可循环切换4种灯光效果；短按白光常亮、暖色呼吸灯及关闭灯光；双击红色爆闪。

7. 低音加/减键：短按/长按低音加/减（共10级）。

8. AUX接口：可插入直径3.5mm立体头的音频线外接音源设备，兼容手机、电脑、平板设备。

9. USB接口：插入USB可播放U盘音乐,支持MP3/WAV格式，最大支持32GB。

10. TF卡槽：插入TF卡可播放里面的音频文件，支持MP3/WAV格式，最大支持32GB。

11. Type-C接口：可连接外部充电线为设备充电。

产品参数

产品型号:	SD-P14
蓝牙版本:	5.3
充电接口:	TYPE-C
充电输入:	5V⎓2A
额定功率:	50W
播放时间:	16级音量（灯光开启）约4小时; iPhone 8级音量（灯光开启）约7小时
充电时间:	约6小时
扬声器阻抗:	4Ω/ 25W ~ 8Ω/15W
电池容量:	7.4V/5200mAh
待机时间:	300天（蓝牙关闭）
传输距离:	≧10米
产品尺寸:	长190x高100x宽99 (毫米)
配　　件:	Type-C 数据线，AUX 音频线，说明书

本保修不适用于以下情况

A. 已超出保修期的产品；

B. 因在说明所允许或预期用途之外使用产品而造成的损坏；

C. 未经授权而被拆卸、修理或改装过的产品；

D. 无法出示保修卡和购买凭证的情况；

E. 由外部原因及自然灾害（包括地震、火灾等）造成的损坏。

注： 本保修不包含产品运输费用，且不提供上门维修服务

产品注意事项

1.为保证锂电池使用寿命，建议使用完再充电，频繁充电将加速电池芯片老化，长时间不用时应每隔两个月充一次电;
2.因喇叭磁性较强，不可将机器和银行卡等带磁性的东西放一起，以免造成失磁而带来不必要的麻烦;
3.本产品所有配件皆按本机工作需要设计，如需更换配件尽量使用本公司原装配件，以 达到最佳工作状态;
4.本产品在充电和正常使用过程中可能会轻微变热，这属于正常现象;
5.请使用抗静电软布来清洁擦拭本产品，在清洁本产品时请先关闭电源开关，并断开所有外部连接。请勿用化学物质擦拭(如:酒精、苯等化学洗剂或有磨砂性的清洁擦拭剂);
6.请勿摔落、抛掷或者踩踏本产品，请勿擅自拆解本产品，否则不能享受本公司的免费保修服务;
7.符合“微功率短距离无线电发射设备目录和技术要求”的具体条款和使用场景，采用的天线类型和性能，控制、调整及开关等使用方法;
8.不得擅自改变使用场景或使用条件、扩大发射频率范围、加大发射功率(包括额外加装射频功率放大器)，不得擅自更改发射天线;
9.不得对其他合法的无线电台(站)产生有害干扰，也不得提出免受有害干扰保护;
10.应当承受辐射射频能量的工业、科学及医疗(ISM)应用设备的干扰或其他合法的无线电台(站)干扰;
11.如对其他合法的无线电台(站)产生有害干扰时，应立即停止使用，并采取措施消除干扰后方可继续使用;
12.在航空器内和依据法律法规、国家有关规定、标准划设的射电天文台、气象雷达站、卫星地球站(含测控、测距、接收、导航站)等军民用无线电台(站)、机场等的电磁环境保护区域内使用微功率设备，应当遵守电磁环境保护及相关行业主管部门的规定;
13.禁止在以机场跑道中心点为圆心、半径5000米的区域内使用各类模型遥控器
14.微功率设备使用时温度和电压的环境条件。
15.制造型号:SD-P14。

产品保修卡

购买产品时，请认真填写此卡，并予以妥善保存。

用户档案

用户姓名	
性别	
通讯地址	
邮编	
联系电话	
购买地点	
购买日期	
品名及规格	
销售单号	
机身编号	
经销商签名	
用户签名	

中国制造

经销商盖章处

SHIDU



SD-P14

PORTABLE SPEAKER

USER MANUAL

PRODUCT DIMENSION DRAWING



PRECAUTIONS

Batteries(battery packs or combined batteries) shall not be exposed to such as sunlight,fire or similar overheating environment.If the battery is not replaced properly there will be a risk of explosion,so please replace it with the same type or equivalent type of battery.This product does not come with a power adapter,consumers should purchase a power adapter that is certified and meets the standard requirements when charging it through a power adapter.

PRODUCTINTRODUCTION

Speaker function button diagram





1. Mode switch key
2. TWS pairing key
3. Multifunction Control Key
4.Treble Increase/ Treble Decrease
5.Battery Level Key
6. Light Key
7. Bass Increase / Bass Decrease
8.AUX Port
9. USB Port
10. TF Card
11. Type-C Port

OPERATION GUIDE

Speaker function button description

1. Mode switch key：Short press to switch (Bluetooth/USB/TF card/LINE).

2. TWs pairing key：Short press to disconnect Bluetooth and re-enter pairing mode; Press and hold the Bluetooth button on one device for 2 seconds,Enter TWS pairing or disconnect.

3. Multifunction Control Key：Long press (middle button for 2 seconds) to turn on/off; Click (middle key) to pause/play/answer incoming calls Listen/ hang up; Push up and down (previous/next song); Push left and right (adjust volume).

4. Treble Increase/Treble Decrease：Short press/long press high tone up/ down (10 levels in total).

5. Battery Level Key: Short press to display battery level, which will automatically turn off after 5 seconds.

6. Light Key: Four types of lighting effects can be cyclically switched; Short press to keep white light on, warm breathing light, and turn off the light;Double click on the red flashing light.

7. Bass Increase: Short press/long press bass up/down (10 levels in total).

8. AUX Port: Supports connecting external audio devices with a 3.5mm stereo jack, also compatible withCompatible with mobile phones, computers, and tablet devices.

9. USB Port：Insert a USB drive to play music, supporting MP3/WAV formats, with a maximum capacity of Hold 32GB.

10.TF Card：Insert TF card to play audio files inside, supports MP3/WAV format, maximum support 32GB.

11.Type-C Port：Connects to an external charging cable to power the device.

PRODUCT PARAMETERS

Product Model:	SD-P14
Bluetooth version:	5.3
Charging port:	TYPE-C
Charging input:	5V⎓2A
Rated power	50W
Playback time:	16-Level Volume is About 4 Hours with Light iPhone 8-Level Volume is About 7 Hours with Light
Charging time:	About 6H
Speaker Impedance:	4Ω/ 25W ~ 8Ω/15W
Battery capacity:	7.4V/5200mAh
Standby time:	300 Days (Bluetooth Off)
Transmission distance:	≧10米
Product sise:	W190xH100xD99(mm)
Accessories:	Type-C Cable, AUX Cable,Instruction book

THIS WARRANTY DOES NOTAPPLY

A.To a product that is out of warranty;

B.To damage caused by operatingthe product outside the permitted or intended uses described by;

C.To a product that has been disassembled,repaired or refitted without the authorization;

D.Ifwarranty card and proofof purchase cannot be presented;

E.To damage caused by external causes and naturaldisasters,including earthquakes,fire,etc.

Note. The warranty does not include product transport costs and does not provide onsite maintenance services.

SHIDU After sales service:

If you have any questions, please feel free to contact us, we will try our best to provide best service.
WWW.10shidu.com Email: service@ 10shidu.com

Made in China

注意:
本手册描述的产品及其附件的某些特征和功能，仅供参考。十度数码科技保留随时修改本手册中任何信息的权利，无需进行任何提前通知且不承担任何责任。

无担保声明:
本手册中的内容，除非适用法律要求，十度数码科技对本手册中的所有内容不提供任何明示或暗示的保证。
在法律允许的范围内，十度数码科技在任何情况下，都不对因使用本手册相关内容而产生的任何特殊的、附带的、间接的、继发性的损害进行赔偿，也不对任何利润、数据、商誉或可预期的损失进行赔偿。

进出口管制:
若需将此产品手册中描述的产品出口、再出口、或者进口，您应遵守适用的进出口管制法律法规。

深圳市十度数码科技有限公司 Shenzhen SHIDU Digital Co.,Ltd
地址:深圳市宝安区福海街道和平社区新兴工业园二区第八栋
电话:0755 - 21635866　传真:0755 - 29105099
全国统一服务热线 4008 939 488
官方网址 WWW.10SHIDU.COM

本说明书所示产品图片及文字功能已经详细核对，如出现印刷错漏，本公司不承担因此产生的后果，产品图片及详细功能参数请以实物为准。
“SHIDU”“十度”“10”均已注册商标，受知识产权保护，未经本公司允许不得仿冒，违者必究。
本公司保留对产品原正改进的权利，届时恕不另行通知，在法律允许范围内，最终解释权归深圳市十度数码科技有限公司所有。